Integrated phased-array 1×16 photonic switch for WDM optical packet switching application

Citation for published version (APA):

Soganci, I. M., Tanemura, T., Williams, K. A., Calabretta, N., Vries, de, T., Smalbrugge, E., Smit, M. K., Dorren, H. J. S., & Nakano, Y. (2009). Integrated phased-array 1×16 photonic switch for WDM optical packet switching application. In *Proceedings of the International Conference on Photonics in Switching 2009. PS '09, 15-19 September 2009, Pisa, Italy* (pp. We13-1/2). Institute of Electrical and Electronics Engineers.
<https://doi.org/10.1109/PS.2009.5307760>

DOI:

[10.1109/PS.2009.5307760](https://doi.org/10.1109/PS.2009.5307760)

Document status and date:

Published: 01/01/2009

Document Version:

Publisher's PDF, also known as Version of Record (includes final page, issue and volume numbers)

Please check the document version of this publication:

- A submitted manuscript is the version of the article upon submission and before peer-review. There can be important differences between the submitted version and the official published version of record. People interested in the research are advised to contact the author for the final version of the publication, or visit the DOI to the publisher's website.
- The final author version and the galley proof are versions of the publication after peer review.
- The final published version features the final layout of the paper including the volume, issue and page numbers.

[Link to publication](#)

General rights

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal.

If the publication is distributed under the terms of Article 25fa of the Dutch Copyright Act, indicated by the "Taverne" license above, please follow below link for the End User Agreement:

www.tue.nl/taverne

Take down policy

If you believe that this document breaches copyright please contact us at:

openaccess@tue.nl

providing details and we will investigate your claim.

Integrated Phased-Array 1x16 Photonic Switch for WDM Optical Packet Switching Application

I. M. Soganci¹, T. Tanemura¹, K. A. Williams², N. Calabretta², T. de Vries², E. Smalbrugge², M. K. Smit², H. J. S. Dorren², and Y. Nakano¹

1: Research Center for Advanced Science and Technology, University of Tokyo, 4-6-1 Komaba, Meguro-ku, 153-8904, Tokyo, Japan

2: COBRA Research Institute, Eindhoven University of Technology, 5600 MB, Eindhoven, The Netherlands

Abstract: Integrated InP/InGaAsP phased-array 1x16 optical switch is fabricated and characterized for broadband WDM optical packet switching. Wavelength-insensitive operation covering the C-band and penalty-free transmission of 40-Gbps signal are demonstrated.

Keywords: Transparent optical switches, integrated photonics, optical packet switching, phased arrays.

1. Introduction

Optical packet switching (OPS) is a possible solution to the problem of power consumption and cost in the future high-capacity optical communication networks. In particular, broadband OPS using wavelength-division multiplexed (WDM) payloads is an attractive scheme to obtain low-latency high-throughput switching with relatively small number of ports [1-4]. For the WDM-OPS application, wavelength-independent large-scale switches are required and have been studied extensively [3,4].

We have recently succeeded in fabricating the first monolithically integrated high-speed 1x16 optical switch based on the phased-array scheme [5], which should theoretically offer wavelength-independent operation. The initial characteristics of the switch were promising with average extinction ratio of 17.0 dB and reconfiguration time less than 6 ns.

Here, we investigate the applicability of our 1x16 switch to broadband WDM-OPS systems for the first time. We successfully demonstrate wavelength-insensitive operation with less than 0.8-dB wavelength-dependent loss across the entire C-band for all output ports. Penalty-free transmission of a 40-Gbps non-return-to-zero (NRZ) signal is also confirmed experimentally.

2. Design and fabrication of the switch

The integrated 1x16 optical phased-array switch consists of two star couplers, an input waveguide, 24 arrayed waveguides with phase shifters and 16 output waveguides (Figure 1a). The optical mode distribution at the output plane is engineered via constructive and destructive interference by controlling the phase shifters at the array section independently. Thus, the signal is switched to a selected output at a certain configuration of electrical signals. We calculated the optimal design parameters using the effective index approximation, beam-propagation method and Fourier optics. In order to achieve wavelength-independent operation, we designed all arrayed waveguides to have

equal length, so that the path-length-difference-based perturbation to the phase distribution was eliminated [6].

The entire chip consists of shallowly etched ridge waveguide with InP/InGaAsP p-i-n double hetero-junction structure. Bulk InGaAsP Q1.3 guiding layer was employed to achieve efficient phase modulation through either the carrier-injection or electro-optical effect. The device was fabricated using single-step metal-organic vapour phase epitaxy (MOVPE) growth and standard dry-etching techniques [5]. Figure 1b shows the scanning electron microscope (SEM) image of the fabricated switch affixed and wire-bonded on a chip carrier. The total footprint of the switch is 4.1 mm x 2.6 mm. Further reduction in device size should be possible with the use of deeply etched high-mesa waveguides.

Figure 1 : Mask layout of the 1x16 optical switch (a) and the SEM image of the fabricated device after wire-bonding (b). The device size is 4.1 mm x 2.6 mm.

3. Characterization of the switch

Continuous-wave light from a wavelength-tunable laser was injected to the switch with transverse-electric (TE) polarization mode. First, the driving voltage conditions for all the 16 switching states were found iteratively by sweeping the DC voltages to the 24 phase shifters. The conditions were optimized using a 1.55- μm -wavelength signal and were not modified for other wavelengths throughout the experiment. The wavelength sensitivity of the switch was then measured by sweeping the wavelength of the laser between 1530 nm and 1565 nm. As example cases, Fig. 2 presents the optical power measured at the outputs versus the signal wavelength in State 11 and State 16. The power values are normalized to the maximum value for clear view of the crosstalk levels. We obtained similar characteristics for all the 16 states and confirmed the wavelength-dependent loss to be less than 0.8 dB for all cases. The crosstalk suppression ratio is better than 8.9 dB across the entire C-band for all cases. Since the facets were not antireflection-coated, we observed small Fabry-Perot oscillations in the output power. The peak-to-valley ratio of these oscillations is between 1.5 and 2 dB, corresponding to an estimated on-chip loss of lower than 7 dB for all switching states.

Figure 2 : Normalised optical power at the outputs when the switch is at State 11 (a) and State 16 (b).

Finally, we measured the bit-error-rate (BER) characteristics of the switch using a 40-Gb/s NRZ pseudorandom bit sequence (PRBS) optical signal at 1.55- μm wavelength. Figure 3 shows the BER curves and eye diagrams of the

output signal at State 1, State 9, and State 16. Clear eye-openings and penalty-free transmission were confirmed in all cases.

Figure 3: BER characteristics and eye-diagrams of the transmitted 40-Gbps NRZ signal in State 1, 9, and 16.

4. Conclusion

We have fabricated and experimentally investigated the wavelength sensitivity of a monolithically integrated InP/InGaAsP phased-array 1x16 optical switch. The device switches to all outputs in the entire C-band (1530-1565 nm) with the wavelength-dependent loss smaller than 0.8 dB. From the Fabry-Perot oscillations between the facets, the on-chip loss was estimated to be less than 7 dB at all outputs. Penalty-free switching of a 40-Gb/s NRZ signal was also confirmed.

5. References

- [1] A. Schaham, B. A. Small, O. L. Ladouceur, and K. Bergman: "A fully implemented 12x12 data vortex optical packet switching interconnection network," *J. Lightwave Technol.*, vol. 23, no. 10, pp. 3066-3075, 2005.
- [2] H. Furukawa, N. Wada, N. Takezawa, K. Nashimoto, and T. Miyazaki: "640 (2x32 λ x10) Gbit/s polarization- multiplexed, wide-colored optical packet switching achieved by polarization-independent high-speed PLZT switch," *Conference on Optical Fiber Communication*, San Diego, California, 2008.
- [3] Y. Kai, et al: "A compact and lossless 8x8 SOA gate switch subsystem for WDM optical packet interconnections," *European Conference on Optical Communication*, Brussels, Belgium, 2008.
- [4] K. A. Williams, et al.: "Integrated optical 2x2 switch for wavelength multiplexed interconnects," *IEEE J. Sel. Top. Quantum Electron.*, vol. 11, no. 1, pp. 78-85, 2005.
- [5] I. M. Soganci, et al.: "High-Speed 1x16 Optical Switch Monolithically Integrated on InP," submitted to *European Conference on Optical Communication*, Vienna, Austria, 2009.
- [6] T. Tanemura and Y. Nakano: "Design and scalability analysis of optical phased-array 1xN switch on planar lightwave circuit," *IEICE Electron. Express*, vol. 5, no. 16, pp. 603-609, 2008.