Wired and wireless multi-service transmission over 1mm-core GI-POF for in-home networks

Citation for published version (APA):

Visani, D., Shi, Y., Okonkwo, C. M., Yang, H., Boom, van den, H. P. A., Tartarini, G., Tangdiongga, E., & Koonen, A. M. J. (2011). Wired and wireless multi-service transmission over 1mm-core GI-POF for in-home networks. *Electronics Letters*, 47(3), 203-204. <https://doi.org/10.1049/el.2010.7273>

DOI:

[10.1049/el.2010.7273](https://doi.org/10.1049/el.2010.7273)

Document status and date:

Published: 01/01/2011

Document Version:

Publisher's PDF, also known as Version of Record (includes final page, issue and volume numbers)

Please check the document version of this publication:

- A submitted manuscript is the version of the article upon submission and before peer-review. There can be important differences between the submitted version and the official published version of record. People interested in the research are advised to contact the author for the final version of the publication, or visit the DOI to the publisher's website.
- The final author version and the galley proof are versions of the publication after peer review.
- The final published version features the final layout of the paper including the volume, issue and page numbers.

[Link to publication](#)

General rights

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal.

If the publication is distributed under the terms of Article 25fa of the Dutch Copyright Act, indicated by the "Taverne" license above, please follow below link for the End User Agreement:

www.tue.nl/taverne

Take down policy

If you believe that this document breaches copyright please contact us at:

openaccess@tue.nl

providing details and we will investigate your claim.

Wired and wireless multi-service transmission over 1mm-core GI-POF for in-home networks

D. Visani, Y. Shi, C.M. Okonkwo, H. Yang, H.P.A. van den Boom, G. Tartarini, E. Tangdiongga and A.M.J. Koonen

Simultaneous transmission of broadband wired and wireless signals over 50 m 1mm-core GI-POF is demonstrated for the first time. 2.2 Gbit/s DMT and 528 MHz 200Mbit/s UWB wireless signals are delivered with $\text{BER} < 10^{-3}$ and $\text{EVM} < 15.5\%$, respectively, in accordance with WiMedia standards.

Introduction: Delivery of multiple services through in-home networks does, of necessity, require increased bandwidth. The transmission capacity needed for delivering current and emerging home services can even exceed the access line capacity [1]. Currently, a plethora of delivery methods and cable media are employed for different kinds of services; e.g. coaxial cable for video broadcast, Cat-5 cable for computer data, twisted pair cable for wired telephony, and wireless LAN for Internet. Such multiple network infrastructures lead to a complicated consumer experience and high service and maintenance costs.

To provide a simplified and easily upgradable in-home network, a single common backbone infrastructure is required, as shown in Fig. 1. Whilst singlemode fibre has been considered as a future-proof transmission medium for optical networks, the associated hardware, installation and maintenance costs are prohibitive for mass deployment for brownfield access and in-building networks. Hence, for cost-sensitive in-home networks other solutions should be considered.

Fig. 1 In-home POF infrastructure for converged transport of wired and wireless services

Plastic optical fibre (POF) is potentially a cost-effective solution, especially when sharing the existing ducts with electrical power line cables [2]. Specifically, Ø1 mm core poly-methylmetacrylate (PMMA) POF is becoming increasingly important, owing to the high potential for 'do-it-yourself' installation, easy maintenance and tolerance to bending.

A comprehensive study on large-core POF systems has been carried out to achieve multi-gigabit transmission [3], and to transport broadband wireless signals [4]. This Letter presents, for the first time, simultaneous transmission of broadband baseband and radio frequency (RF) signals using Ø1 mm core PMMA graded-index (GI) POF. We demonstrate the successful transmission of a DMT signal at a data rate of 2.2 Gbit/s and a WiMedia-compliant multi-band (MB) OFDM UWB radio signal at 200 Mbit/s over a 50 m link of PMMA graded-index POF.

Experimental setup and results: The proposed system is based on a simple intensity-modulated direct-detection (IM-DD) optical link. The main bandwidth limitation of the system is attributed to the POF link bandwidth and the optoelectronic components. The photo-receiver in particular has only a 3 dB level bandwidth of 1.4 GHz.

The experimental setup is depicted in Fig. 2. We split the available bandwidth into two separate spectra; for DMT (~0 to 0.8 GHz) and UWB (0.8 to 1.4 GHz) signals. A WiMedia-compliant UWB transmitter generates a real-time MB-OFDM signal centred at 3.96 GHz (TFC6: 3.696–4.224 GHz). Although the standardised full UWB bit rate is 480 Mbit/s, our available UWB transceiver was limited to 200 Mbit/s. To fit within the limited lowpass characteristic of the POF, downconversion

of the UWB signal from the RF to an intermediate frequency band (0.836–1.364 GHz) is required. To demonstrate the potential of real implementation, a sampling speed of 1.6 GSamples/s is used at the arbitrary waveform generator (AWG) to generate the DMT signal. A bit and power-loading algorithm is used to optimise the signal constellation format for every subcarrier.

Fig. 2 Experimental setup for simultaneous transmission of DMT and UWB signals over POF

Inset: Spectral allocation of DMT and UWB in available bandwidth

The electrically combined signal is used to directly modulate a VCSEL at 667 nm with an eye safe optical emitted power of 0 dBm. The VCSEL is followed by Ø1 mm core 50 m PMMA GI-POF and a photo-receiver based on a Ø230 µm Si-APD, followed by a two-stage electrical amplifier with a gain of 40 dB. The detected signal is fed to a digital phosphor oscilloscope (DPO) in order to capture a time-window of the received signal for off-line performance evaluation. The maximum data rate at a bit error rate (BER) below 10^{-3} for DMT and error vector magnitude (EVM) for UWB is measured.

Fig. 3 DMT and UWB performance against DMT and UWB input power

a Against DMT input power

b Against UWB input power

Fig. 3a shows the performance of the two signals with UWB power fixed to -1 dBm while DMT power varies from -7.2 to +2.8 dBm. For DMT power below 0.8 dBm, the UWB EVM performance complies with the standard EVM limit of 15.5%. The recommended operating region is where the difference between the two curves is the largest, i.e. between -4 and 0 dBm. With DMT power fixed to -3.2 dBm, we repeat the experiment by varying the UWB power, as in Fig. 3b. In this case, the recommended region of operation is between the UWB input power of -5 and 0 dBm. In particular, we set the DMT and UWB signal power to -3.2 and -1 dBm, respectively, to

achieve 2.2 Gbit/s DMT transmission with the UWB EVM below 13%. In Fig. 4, the received constellation for the subcarriers of the DMT signal with 3 bits allocated is shown. In addition, the QPSK constellation of the demodulated UWB signal is shown. Both constellation plots indicate the excellent quality of the received signals.

Fig. 4 Constellation diagrams of received signals after simultaneous transmission over 50 m POF

Conclusion: We have experimentally demonstrated for the first time a combined transmission of wired and wireless signals over Ø1 mm core 50 m PMMA GI-POF. Two broadband signals are simultaneously transmitted: a 2.2 Gbit/s DMT signal with $\text{BER} < 10^{-3}$, and a 528 MHz WiMedia-compliant UWB signal with $\text{EVM} < 13\%$. This work validates the use of Ø1 mm POF links as a common infrastructure for in-home networks capable of transmitting wired and wireless in-home services. In addition, implementation costs are minimised by employing simple transceivers, IM-DD optical systems, and advanced modulation formats.

Acknowledgment: The authors are grateful for financial support of this work in the EU research programmes FP7 ICT-224521 POF-PLUS and ICT-212352 ALPHA.

© The Institution of Engineering and Technology 2011
16 November 2010

doi: 10.1049/el.2010.7273

One or more of the Figures in this Letter are available in colour online.

D. Visani, Y. Shi, C.M. Okonkwo, H. Yang, H.P.A. van den Boom, E. Tangdiongga and A.M.J. Koonen (COBRA Research Institute, Eindhoven University of Technology, P.O. Box 513, NL-5600 MB, Eindhoven, The Netherlands)

E-mail: davide.visani3@unibo.it

G. Tartarini (DEIS, University of Bologna, viale Risorgimento 2, Bologna 40136, Italy)

D. Visani: Also with DEIS, University of Bologna, Italy

References

- 1 Popov, M.: 'The convergence of wired and wireless services delivery in access and home networks'. Optical Fiber Communication Conf., San Diego, CA, USA, 2010, paper OWQ6
- 2 Koonen, A.M.J., van den Boom, H.P.A., Tangdiongga, E., Jung, H.D., and Guignard, P.: 'Designing in-building optical fiber networks'. Optical Fiber Communication Conf., San Diego, CA, USA, 2010, paper JThA46
- 3 Charbonnier, B., Urvoas, P., Ouzzif, M., Le Masson, J., Lambkin, J.D., O'Gorman, M., and Gaudino, R.: 'EU project POF-PLUS: gigabit transmission over 50 m of step-index plastic optical fibre for home networking'. Optical Fiber Communication Conf., San Diego, CA, USA, 2009, paper OWR4
- 4 Yang, H., Shi, Y., Wang, W., Okonkwo, C.M., van den Boom, H.P.A., Koonen, A.M.J., and Tangdiongga, E.: 'WiMedia-compliant UWB transmission over 1 mm core diameter plastic optical fibre', *Electron. Lett.*, 2010, **46**, (6), pp. 434–436